



### Basic features

Approval/Conformity	CE WEEE EAC
Basic standard	IEC 60947-5-2

### Display/Operation

Function indicator	yes
Power indicator	no

### Electrical connection

Connection	M12x1-Male, 4-pin, A-coded
Polarity reversal protected	yes
Protection against device mix-ups	yes
Short-circuit protection	yes

### Electrical data

Load capacitance max. at Ue	0.5 $\mu$ F
Min. operating current I <sub>m</sub>	0 mA
No-load current I <sub>o</sub> max., damped	17 mA
No-load current I <sub>o</sub> max., undamped	12 mA
Operating voltage U <sub>b</sub>	10...55 VDC
Output resistance R <sub>a</sub>	33.0 kOhm + D/33.0 kOhm + D
Protection class	II
Rated insulation voltage U <sub>i</sub>	250 V AC
Rated operating current I <sub>e</sub>	200 mA
Rated operating voltage U <sub>e</sub> DC	24 V
Rated short circuit current	100 A
Ready delay t <sub>v</sub> max.	15 ms
Residual current I <sub>r</sub> max.	20 $\mu$ A
Ripple max. (% of U <sub>e</sub> )	15 %
Switching frequency	1000 Hz
Utilization category	DC -13
Voltage drop static max.	2.5 V

### Environmental conditions

Ambient temperature	-25...70 °C
Contamination scale	3
EN 60068-2-27, Shock	Half-sinus, 30 g <sub>n</sub> , 11 ms
EN 60068-2-6, Vibration	55 Hz, amplitude 1 mm, 3x30 min
IP rating	IP68

### Interface

Switching output	PNP normally open/normally closed (NO/NC)
------------------	---

Inductive Sensors  
**BES M18MI2-PAH80B-S04G**  
**Order Code: BES0495**



**Material**

Housing material	Brass, Nickel-free coated
Material sensing surface	PBT

**Mechanical data**

Dimension	Ø 18 x 83 mm
Installation	for flush mounting
Size	M18x1
Tightening torque	25 Nm

**Range/Distance**

Assured operating distance Sa	6.4 mm
Hysteresis H max. (% of Sr)	15.0 %
Rated operating distance Sn	8 mm
Real switching distance sr	8 mm
Repeat accuracy max. (% of Sr)	5.0 %
Switching distance marking	■ ■
Temperature drift max. (% of Sr)	10 %
Tolerance Sr	±10 %

**Remarks**

Flush: See installation instructions for inductive sensors with extended range 939221.  
 The sensor is functional again after the overload has been eliminated.

**Connector Drawings**



**Wiring Diagrams**

